

## Developing Open Form User Models for Rotating Machines and Static Devices in PSLF

April 26, 2007 Pterra, LLC Chicago, Illinois

#### Outline





Introduction


Overview

Development process

Data Collection

Developed Models





From time to time user's models are developed, even if they can be replaced or approximated by models already available, for particular purposes, i.e., research, training or code accessibility.





- Knowledge of equipment performance characteristics (Manufacturer knowledge).
- Understanding of the overall response characteristics of the network where the equipment is connected (Transmission provider or operator).
- Ability to convert the equipment and associated network response characteristics into a usable model for simulation (Model writer).





The success of a user model development depends on the collaborative effort of the:

- Equipment specialist (manufacturer)
- Power system specialist (transmission owner)
- Model code specialist





• Given a good understanding of the control process and software interactions, a close coordination with the equipment manufacturer could help in tuning the simulation response of the user model.





- Writing a user's model is an exercise in practical modeling rather than theoretical.
  - The proper selection of controls and interactions to be included in the model is very important.
  - Higher order frequency effects do not have impact on stability performance.
  - An overly complicated model that captures all frequencies is not better than a **simplified model** that captures the essential response.
  - Robustness response within the time step size is also a very important factor. High frequency effects and voltage-sensitive models can lead to error propagation and numerical problems.






- Power System Equipment is modeled by a set of nonlinear algebraic-differential equations.
- Dynamic performance under disturbances is analyzed by solving this equation set.
- Dynamic simulation of a power system implies two processes:
  - Simulation of dynamic models represented by differential equations (generators, exciters, governors, etc.)
  - Solution of the electrical network represented by algebraic equations (Voltage & Current).





- Any user's model contains all or some of the following modes:
  - o INIT
  - SORC
  - ALGE
  - RATE
  - OUTP
  - NETW







- SORC Mode: Calculates nodal injection currents; i.e., generator network boundary source conditions. Not needed if the model is not connected directly to the network; i.e., exciter or governor models.
- ALGE Mode: Calculates secondary variables (not state variables); i.e., internal signals. Network events are initiated in this mode; such as, load shedding, capacitor switching.





 RATE Mode: State variable derivatives are calculated.

 OUTP Mode: Output variables should be set either in OUTP or ALGE MODE.

 Optionally, the name and scale range for the output channels can be modified in INIT MODE.






- This information is usually provided in Control Block Diagram form that shows I/O parameters and relationship among equipment components.
- Control Block Diagrams contains implicitly the algebraic-differential equations, simply and graphically.

Consulting and Training Services

Pterra

# Sample Salient Pole Synchronous Machine






#### Sample Static Var Device





SVC Model represents a shunt –connected static (no moving parts) device whose output varies to control specific parameters of the power network.







 Control Block Diagram provided by the manufacturer is analyzed according to the simulation objective and the tool for the performance analysis.


Higher frequency response is discarded.






- Initial Conditions (Steady State equations)
  may be written by proceeding from right to
  left, from the output side to the input side of
  the block diagram.
- For instance, the SVC susceptance (Bsvc) at initial condition is calculated from the reactive power source/sink that represents the SVC in the load flow at its terminal voltage.
- At steady state, there is no change or driven variables, all derivatives should be zero.






 Equating to zero all state variable derivatives will complete the initial condition algebraic equations.






 Auxiliary algebraic variables, state variables and derivatives are formulated as a function of the input parameters to each block.





Block diagram of 1st order lag

Initialization Simulation
STATE= Y Derivative = (AX-STATE)/T
X=Y/A Output= STATE







Before testing the model, the code should be inspected to avoid inconsistencies, logical or syntax errors.

 Test the code to the limits by changing input variables to their max/min values and check the feasibility of the results.





#### Summary:

- Revise manufacturer's control block diagram according to the objective and simulation tool.
- Define state variables and assign meaningful names (if possible) to the algebraic variables.
- Understanding the physical meaning of each variable is useful for the code developer.





- Define Input/output format
- Write initial condition equations proceeding from right to left in the block diagram.
- Write simulation equations, i.e., state, derivative and auxiliary variables proceeding from left to right in the block diagram.
- Insert initial conditions and simulation equations into the block modes according to the tool language and associated format.





- Debug the code from syntax and logical errors.
- It is worthy to revise not only the meaning of each variable but also how each variable takes a value, particularly, the initial value.
- None of the above assure a bug-free model.
   Manufacturer and/or user testing are essential to the development process.

#### **Data Collection**





- control block diagram
- V-curve
- saturation curve
- equipment description

## **Developed Models**







- User's dynamic models for PSLF are written in EPCL under generic model types or software interfaces called EPCGEN or EPCMOD.
- EPCMOD interface can represent most power system control functions commonly required for user's models.
- EPCGEN interface is specifically for user's modeling of devices directly connected to the network, i.e. motor, SVC, generator, statcon or current injection models.
- The user's model for the synchronous motors and the SVC for this project were written by using EPCGEN interface.

## Sample PSLF Output










- Close-in fault, cleared normally
- Plot of voltage and angle at salient pole machine

## Sample PSLF Output








- Same fault
- Response at SVC Bsvs

## Sample PSLF Output







- Same fault
- Response at SVC Vreg